



BELLA

DESCRIPTION

Hogar Bella (Bella is a state-of-the art security device that provides two-way communication and delivers High definition video to any device. It acts as a gatekeeper and track of visitors. The Bella also helps you communicate with visitors locally or remotely. The sturdy and well-built Bella can endure any weather conditions. It records the video even if the internet goes down and helps the homeowner to keep an eye on everything near the front door.



NIGHT-VISION SUPPORTED



SUPPORTS VIDEO PLAYBACK



HIGH-RESOLUTION VIDEO



CLEAR AND BIGGER PICTURE



CLOUD STORAGE SUPPORT



LOCK/UNLOCK THE DOOR

SPECIFICATIONS

Transmission Frequency	2.4 GHz
Image Sensor	1/4"Color CMOS Sensor
Image Sensor	H.264
Two-Way Audio	Yes
One-Way Video	Yes
Push Notification	Yes / iOS and Android
Event List	Yes / Snapshot and Video
Playback	App / iOS and Android
Night Vision	Supported(4 IR LED, Night visibility up to 3 meters)
Audio Input/output	Speaker & Microphone

Video Resolution	1080P/720P/VGA
Video FPS	Up To 25FPS
Data Storage	Memory Card up to 128GB
View Angle	H:110/V:90
Wireless Connectivity	Wi-Fi 802.11b/g/n
Inbuilt battery	5000 mAh Li battery
IP Ratings	IP65
Display Resolution	2 Megapixels
Lens	f:2.8 mm, F:2.0 (IR Lens)
Power Consumption	2mW in sleep mode & 1w when wake up
Operating Temperature	10 - 50 °C
Operating Humidity	20% - 85% non-condensing
Communication	Full duplex
Motion Detection	Supports Motion Detection

PREINSTALLATION & CHECKS:

- Ensure that you have a reliable cable internet connection for the Bella to work at its best. Portable Internet connections based on Hot spots or a Wi-Fi Dongle will not provide the best and consistent results.
- Your experience with Bella will vary based on the quality of your router.

APP SET UP & CONFIGURATION

- Download and Install the "Hogar" app on your device.
- Video door bell have two installation methods
 - 1) Power the Bella using a 12V adapter for continuous power supply.
 - 2) Using 5v power supply, In this once the battery gets fully charged we can place the door bell and later again we need to charge when it discharge.
- Press the power button on the rear to turn ON the device.
- Open the Hogar SE application and register for an account if you are a new user.
- Login into the Hogar application and select Room from the dashboard and then + icon on the right top of the screen.
- Select security-->Video doorbell-->Select the option and continue to the next step
- Enter the Wifi Credentials of the Wi-Fi network to connect and select next.
- Point the Bella camera to the application screen to scan the displayed QR Code.
- Bella makes a prompt sound indicating a successful configuration.
- Rename the device and add it to the room.
- Select the Video doorbell to stream live video.

WARRANTY & ENQUIRY

Hogar Provides Limited Warranty of 18 months on every product.

For Orders/Details, kindly reach out to us at info@hogarcontrols.com



Scan QR code for more details and Sales enquiries